

Specifications

Except where noted otherwise, specified values are obtained after warming up the equipment for 30 minutes at a constant ambient temperature and then performing calibration. The typical values are given for reference, and are not guaranteed.

Model	MS2651B	MS2661B	
Frequency	Frequency range	9 kHz to 3 GHz	
	Display frequency accuracy	\pm (display frequency \times reference frequency accuracy + span \times span accuracy + 100 Hz) *Span: ≥ 10 kHz, after calibration	
	Marker frequency display accuracy	Normal: Same as display frequency accuracy, Delta: Same as frequency span accuracy	
	Frequency counter	Resolution: 1 Hz, 10 Hz, 100 Hz, 1 kHz Accuracy: Display frequency \times reference frequency accuracy ± 1 LSD (at S/N: ≥ 20 dB)	
	Frequency span	Setting range: 0 Hz, 1 kHz to 3.1 GHz Accuracy: $\pm 2.5\%$ (span: ≥ 10 kHz)	Setting range: 0 Hz, 1 kHz to 3.1 GHz Accuracy: $\pm 2.5\%$ (span: ≥ 10 kHz) $\pm 5\%$ (span: < 10 kHz with option 02)
	Resolution bandwidth (RBW) (3 dB bandwidth)	Setting range: 1 kHz, 3 kHz, 10 kHz, 30 kHz, 100 kHz, 300 kHz, 1 MHz, 5 MHz (manually settable, or automatically settable according to frequency span) *Option 02 (MS2661B only): 30 Hz, 100 Hz, and 300 Hz are added. Measurements of noise, C/N, adjacent channel power and channel power by measure function are executed with the calculated equivalent noise bandwidth of the RBW. Selectivity (60 dB : 3 dB): $\leq 10:1$ (RBW: 1 to 300 kHz), $\leq 15:1$ (RBW: 1, 5 MHz)	
	Video bandwidth (VBW)	1 Hz to 3 MHz (1-3 sequence), OFF (manually settable, or automatically settable according to RBW)	
	Noise sideband, stability	Noise sideband: ≤ -90 dBc/Hz (1 GHz, 10 kHz offset)	Noise sideband: ≤ -100 dBc/Hz (1 GHz, 10 kHz offset)
		Residual FM: ≤ 20 Hzp-p/0.1 s (1 GHz, span: 0 Hz) Frequency drift: ≤ 200 Hz/min (span: ≤ 10 kHzxn, sweep time: ≤ 100 s) *After 1-hour warm-up at constant ambient temperature	
	Reference oscillator	Frequency: 10 MHz Aging rate: 2×10^{-6} /year (typical); Option 01: 1×10^{-7} /year, 2×10^{-8} /day Temperature characteristics: 1×10^{-5} (typical, 0° to 50°C); Option 01: $\pm 5 \times 10^{-8}$ (0° to 50°C , referenced to 25°C)	
Amplitude	Level measurement	Measurement range: Average noise level to +30 dBm Maximum input level: +30 dBm (CW average power, RF ATT: ≥ 10 dB), ± 50 Vdc	Average noise level: ≤ -115 dBm (1 MHz to 1 GHz), ≤ -115 dBm + f [GHz] dB (> 1 GHz), ≤ -114 dBm (1 MHz to 1 GHz, at Option 08 pre-amplifier installed), ≤ -114 dBm + 1.5f [GHz] dB (> 1 MHz, at Option 08 pre-amplifier installed) *RBW: 1 kHz, VBW: 1 Hz, RF ATT: 0 dB Residual response: ≤ -100 dBm (RF ATT: 0 dB, input: 50Ω termination, 1 MHz to 3 GHz)
	Total level accuracy	± 1.3 dB (100 kHz to 3 GHz) *Level measurement accuracy after calibration using internal calibration signal Total level accuracy: Reference level accuracy (0 to -49.9 dBm) + frequency response + log linearity (0 to -20 dB) + calibration signal source accuracy	
	Reference level	Setting range Log scale: -100 to $+30$ dBm, Linear scale: $224 \mu\text{V}$ to 7.07 V Unit Log scale: dBm, dB μV , dBmV, V, dB μV /m, W, dB μV /m Linear scale: V Reference level accuracy: ± 0.4 dB (-49.9 to 0 dBm), ± 0.75 dB (-69.9 to -50 dBm, 0.1 to $+30$ dBm), ± 1.5 dB (-80 to -70 dBm) *After calibration, at 100 MHz, 1 MHz span (when RF ATT, RBW, VBW, and sweep time set to AUTO) RBW switching uncertainty: ± 0.3 dB (1 kHz to 1 MHz), ± 0.4 dB (5 MHz) *After calibration, referenced to RBW 3 kHz Input attenuator (RF ATT) Setting range: 0 to 70 dB (10 dB steps) *Manually settable, or automatically settable according to reference level Switching uncertainty: ± 0.3 dB (0 to 50 dB), ± 1.0 dB (0 to 70 dB) *After calibration, frequency: 100 MHz, referenced to RF ATT: 10 dB	
	Frequency response	± 0.5 dB (100 kHz to 3 GHz, referenced to 100 MHz, RF ATT: 10 dB, 18° to 28°C) ± 1.5 dB (9 to 100 kHz, referenced to 100 MHz, RF ATT: 10 dB, 18° to 28°C) ± 1.0 dB (100 kHz to 3 GHz, referenced to 100 MHz, RF ATT: 10 to 50 dB)	
	Waveform display	Scale (10 div) Log scale: 10, 5, 2, 1 dB/div Linear scale: 10, 5, 2, 1%/div Linearity (after calibration) Log scale: ± 0.4 dB (0 to -20 dB, RBW: ≤ 1 MHz), ± 1.0 dB (0 to -70 dB, RBW: ≤ 100 kHz), ± 1.5 dB (0 to -85 dB, RBW: ≤ 3 kHz), ± 2.5 dB (0 to -90 dB, RBW: ≤ 3 kHz) Linear scale: $\pm 4\%$ (compared to reference level) Marker level resolution Log scale: 0.01 dB, Linear scale: 0.02% of reference level	
	Spurious response	2nd harmonic distortion: ≤ -55 dBc (10 to 100 MHz), ≤ -60 dBc (0.1 to 1.5 GHz) *Mixer input: -30 dBm Two signals 3rd order intermodulation distortion: ≤ -70 dBc (10 MHz to 3 GHz) *Frequency difference of two signals: ≥ 50 kHz, mixer input: -30 dBm	2nd harmonic distortion: ≤ -60 dBc (10 to 200 MHz), ≤ -75 dBc (0.2 to 1.5 GHz), ≤ -80 dBc (0.8 to 1 GHz) *Mixer input: -30 dBm Two signals 3rd order intermodulation distortion: ≤ -70 dBc (10 to 100 MHz), ≤ -80 dBc (0.1 to 3 GHz) *Frequency difference of two signals: ≥ 50 kHz, mixer input: -30 dBm

Model		MS2651B	MS2661B
Amplitude	1 dB gain compression	≥-5 dBm (≥100 MHz, at mixer input)	
	Maximum dynamic range	1 dB gain compression level to average noise level: >105 dB (0.1 to 1 GHz), >105 dB - f [GHz] dB (>1 GHz) Distortion characteristics (RBW: 1 kHz) 2nd harmonic: >67.5 dB (10 to 100 MHz), >70 dB (100 to 500 MHz), >70 - f [GHz] dB (0.5 to 1 GHz) 3rd order intermodulation: >76.6 dB (10 MHz to 1 GHz), >76.6 - (2/3)f [GHz] dB (1 to 3 GHz)	1 dB gain compression level to average noise level: >110 dB (0.1 to 1 GHz), >110 dB - f [GHz] dB (>1 GHz), >109 dB (0.1 to 1 GHz, at Option 08 pre-amplifier installed), >109 dB - 1.5f [GHz] (>1 GHz, at Option 08 pre-amplifier installed) Distortion characteristics (RBW: 1 kHz) 2nd harmonic: >72.5 dB (10 to 200 MHz), >80 dB (200 to 500 MHz), >80 - f [GHz] dB (0.5 to 1.5 GHz), >82.5 - f [GHz] dB (0.8 to 1 GHz) 3rd order intermodulation: >80 dB (10 to 100 MHz), >83.3 dB (0.1 to 1 GHz), >83.3 - (2/3)f [GHz] dB (1 to 3 GHz)
Sweep	Sweep time	Setting range: 20 ms to 1000 s (Manually settable, or automatically settable according to span, RBW, and VBW) Accuracy: ±15% (20 ms to 100 s), ±45% (110 to 1000 s), ±1% (time domain sweep: digital zero span mode)	
	Sweep mode	Continuous, single	
	Time domain sweep mode	Analog zero span, digital zero span	
	Zone sweep	Sweeps only in frequency range indicated by zone marker	
	Tracking sweep	Sweeps while tracing peak points within zone marker (zone sweep also possible)	
Functions	Number of data points	501	
	Detection mode	NORMAL: Simultaneously displays max. and min. points between sample points POS PEAK: Displays max. point between sample points NEG PEAK: Displays min. point between sample points SAMPLE: Displays momentary value at sample points Detection mode switching uncertainty: ±0.5 dB (at reference level)	
	Display	Color TFT-LCD, Size: 5.5", Number of colors: 17 (RGB, each 64-scale settable), intensity adjustment: 5 steps settable	
	Display functions	Trace A: Displays frequency spectrum Trace B: Displays frequency spectrum Trace Time: Displays time domain waveform at center frequency Trace A/B: Displays Trace A and Trace B simultaneously. Simultaneous sweep of same frequency, alternate sweep of independent frequencies Trace A/BG: Displays frequency region to be observed (background) and object band (foreground) selected from background with zone marker simultaneously at alternate sweep Trace A/Time: Displays frequency spectrum, and time domain waveform at center frequency simultaneously at alternate sweep Trace move/calculation: A→B, B→A, A↔B, A+B→A, A-B→A, A-B+DL→A	
	Storage functions	NORMAL, VIEW, MAX HOLD, MIN HOLD, AVERAGE, CUMULATIVE, OVER WRITE	
	FM demodulation waveform display function	Demodulation range: 2, 5, 10, 20, 50, 100, 200 kHz/div Marker display accuracy: ±5% of full scale (referenced to center frequency, DC-coupled, RBW: 5 MHz, VBW: 1 Hz, CW) Demodulation frequency response: DC (50 Hz at AC-coupled) to 100 kHz *Range: ≤20 kHz/div, VBW: OFF, at 3 dB bandwidth DC (50 Hz at AC-coupled) to 500 kHz *Range: ≥50 kHz/div, VBW: OFF, at 3 dB bandwidth *RBW: ≥100 kHz usable	
	Input connector	N-J, 50 Ω	
	Auxiliary signal input and output	IF OUTPUT: 455 kHz (RBW: ≤30 kHz), 10.695 MHz (RBW: ≥100 kHz), BNC connector VIDEO OUTPUT (Y): 0 to 0.5 V ±0.1 V (100 MHz, from lower edge to upper edge at 10 dB/div or 10%/div, 75 Ω terminated, BNC connector) COMPOSITE OUTPUT: For NTSC, 1 Vp-p (75 Ω terminated), BNC connector EXT REF INPUT: 10 MHz ±10 Hz, ≥0 dBm (50 Ω terminated), BNC connector	
	Signal search	AUTO TUNE, PEAK→CF, PEAK→REF, SCROLL	
	Zone marker	NORMAL, DELTA	
	Marker →	MARKER→CF, MARKER→REF, MARKER→CF STEP SIZE, ΔMARKER→SPAN, ZONE→SPAN	
	Peak search	PEAK, NEXT PEAK, NEXT RIGHT PEAK, NEXT LEFT PEAK, MIN DIP, NEXT DIP	
	Multimarker	Number of markers: 10 max. (HIGHEST 10, HARMONICS, MANUAL SET)	
	Measure	Noise power (dBm/Hz, dBm/ch), C/N (dBc/Hz, dBc/ch), occupied bandwidth (power N% method, X-dB down method), adjacent channel power (REF: total power/reference level/in-band level method, channel designate display: 2 channels × 2 graphic display), average power of burst signal (average power in designated time range of time domain waveform), channel power (dBm, dBm/Hz), template comparison (upper/lower limits × each 2, time domain), MASK (upper/lower × each 2, frequency domain)	
	Save/recall	Saves and recalls setting conditions and waveform data to internal memory (max. 12) or memory card	
Hard copy	Printer (HP dotmatrix, EPSON dotmatrix or compatible models): Display data can be hard-copied via RS-232C, GPIB and Centronics (Option 10) interface Plotter (HP-GL, GP-GL compatible models): Display can be output via RS-232C and GPIB interface		

Model		MS2651B	MS2661B
Functions	PTA	Language: PTL (interpreter based on BASIC) Programming: Using editor of external computer Program memory: Memory card, upload/download to/from external computer Programming capacity: 192 KB Data processing: Directly accesses measurement data according to system variables, system subroutines, and system functions	
	RS-232C	Outputs data to printer and plotter. Control from external computer (excluding power switch)	
	GPIB	Meets IEEE488.2. Controlled by external computer (excluding power switch). Or controls external equipment with PTA Interface function: SH1, AH1, T6, L4, SR1, RL1, PP0, DC1, DT1, C1, C2, C3, C4, C28	
	Correction	Automatic correction of insertion loss of MA1621A Impedance Transformer Correction accuracy (RF ATT: ≥ 10 dB): ± 2.5 dB (9 to 100 kHz), ± 1.5 dB (100 kHz to 2 GHz), ± 2.0 dB (2 to 3 GHz) *Typical value Antenna correction coefficients: Correct display and measurement of field strengths (dB μ V/m) for specified antennas, Internal antenna correction coefficients (MP534A/651A Dipole Antenna, MP635A/666A Log-Periodic Antenna, MP414B Loop Antenna, and four antennas user-defined; writes via GPIB or RS-232C interface, saves/loads to/from memory card)	
	Memory card interface	Functions: Saving/recalling measurement parameters/waveform data, uploading/downloading PTA programs; Applicable cards: SRAM, EPROM, Flash EPROM *Only SRAM writable; Card capacity: 2 MB max. Connector: PCMCIA Rel. 2.0, 2 slots	
Others	Conducted emission	Meets the EN55011 (Group 1, Class A)	
	Radiated emission	Meets the EN55011 (Group 1, Class A)	
	Static discharge	Meets the EN50082-1	
	Radiation field	Meets the EN50082-1	
	Conducted susceptibility	Meets the IEC801-4 (Level II)	
	Vibration	Meets the MIL-STD-810D	
	Power (operating range)	85 to 132/170 to 250 Vac (automatic voltage switching), 47.5 to 63 Hz, 380 to 420 Hz (85 to 132 Vac only), ≤ 320 VA	
	Dimensions and mass	320 (W) \times 177 (H) \times 351 (D) mm, ≤ 10.8 kg (without option)	
	Ambient temperature	0° to +50°C (operate), -40° to +75°C (storage)	

●Option 01: Reference crystal oscillator

Frequency	10 MHz
Aging rate	$\leq 1 \times 10^{-7}$ /year, $\leq 2 \times 10^{-8}$ /day (after power on, with reference to frequency after 24 h)
Temperature characteristics	$\pm 5 \times 10^{-8}$ (0° to 50°C, with reference to 25°C)
Buffer output	BNC connector, 10 MHz, > 2 Vp-p (200 Ω terminated)

●Option 02: Narrow resolution bandwidth (MS2661B only)

Resolution bandwidth (3 dB)	30 Hz, 100 Hz, 300 Hz
Resolution bandwidth switching uncertainty	± 0.4 dB (RBW 3 kHz referenced)
Selectivity (60 dB:3 dB)	$\leq 15:1$ (RBW: 100, 300 Hz), $\leq 20:1$ (RBW: 30 Hz)

●Option 04: High-speed time domain sweep

Sweep time	12.5 μ s, 25 μ s, 50 μ s, 100 to 900 μ s (one most significant digit settable) 1.0 to 19 ms (two upper significant digits settable)
Accuracy	$\pm 1\%$
Marker level resolution	0.1 dB (log scale), 0.2% (linear scale, relative to reference level)

●Option 06: Trigger/gate circuit

Trigger switch	FREERUN, TRIGGERED	
Trigger source	EXT	Trigger level: ± 10 V (resolution: 0.1 V), TTL level Trigger slope: Rise/Fall Connector: BNC
	VIDEO	Trigger level (at log scale): -100 to 0 dB (resolution: 1 dB) Trigger slope: Rise/Fall
	WIDE IF VIDEO	Trigger level: High, middle, or low selectable Bandwidth: ≥ 20 MHz Trigger slope: Rise/Fall
	LINE	Frequency: 47.5 to 63 Hz (line lock)
	TV	Method: M-NTSC, B/G/H PAL Sync: V-SYNC, H-SYNC Sync line (NTSC) H-SYNC (ODD): 7 to 262 line, H-SYNC (EVEN): 1 to 263 line Sync line (PAL) H-SYNC (ODD): 1 to 312 line, H-SYNC (EVEN): 317 to 625 line *Option 16 required

Trigger delay	Pre-trigger (displays waveform from previous max. 1 screen at trigger occurrence point) Range: -time span to 0 s Resolution: time span/500 Post trigger (displays waveform from after max. 65.5 ms at trigger occurrence point) Range: 0 to 65.5 ms Resolution: 1 μ s
Gate sweep	In frequency domain, displays spectrum of input signal in specified gate interval Gate delay: 0 to 65.5 ms (from trigger point, resolution: 1 μ s) Gate width: 2 μ s to 65.5 ms (from gate delay, resolution: 1 μ s)

● **Option 07: AM/FM demodulator**

Voice output	With internal loudspeaker and earphone connector (ϕ 3.5 jack), adjustable volume
---------------------	--

● **Option 08: Pre-amplifier*1**

Frequency range	100 kHz to 3 GHz, 100 kHz to 2.5 GHz (with Option 22)	
Noise figure	≤ 7 dB (typical, < 2 GHz), ≤ 12 dB (typical, ≥ 2 GHz), ≤ 9 dB (typical, < 2 GHz, with Option 22), ≤ 14 dB (typical, ≥ 2 GHz, with Option 22)	
Amplitude	Measurement range	Average noise level to +10 dBm
	Max. input level	CW average power: +10 dBm, ± 50 Vdc
	Average noise level	MS2651B: ≤ -130 dBm (1 MHz to 1 GHz), ≤ -130 dBm + 1.5f [GHz] dB (> 1 GHz) MS2661B: ≤ -134 dBm (1 MHz to 1 GHz), ≤ -134 dBm + 2f [GHz] dB (> 1 GHz), ≤ -132 dBm (1 MHz to 1 GHz, with Option 22), ≤ -132 dBm + 2f [GHz] dB (≥ 1 GHz, with Option 22) *RBW: 1 kHz, VBW: 1 Hz, RF ATT: 0 dB
	Reference level	Setting range Log scale: -120 to +10 dBm, or equivalent level Linear scale: 22.4 μ V to 707 mV, 27.4 μ V to 487 mV with Option 22 Reference level accuracy: ± 0.5 dB (-69.9 to -20 dBm), ± 0.75 dB (-89.9 to -70 dBm, -19.9 to +10 dBm) *After calibration, referenced to 100 MHz, 1 MHz span (RF ATT, RBW, VBW, and sweep time set to AUTO) RBW switching uncertainty: ± 0.5 dB (after calibration, referenced to 3 kHz RBW) RF ATT switching uncertainty: ± 0.5 dB (0 to 50 dB), ± 1.0 dB (0 to 70 dB) *After calibration, referenced to 100 MHz, RF ATT: 10 dB
	Frequency response	± 2.0 dB (100 kHz to 3 GHz, referenced to 100 MHz, RF ATT: 10 to 50 dB) ± 2.0 dB (with Option 22, 100 kHz to 2.5 GHz, referenced to 100 MHz, RF ATT: 10 dB, 18° to 28°C)
	Linearity of waveform display	Log scale (after calibration): ± 0.5 dB (0 to -20 dB), ± 1.0 dB (0 to -60 dB), ± 1.5 dB (0 to -75 dB) Linear scale (after calibration): $\pm 5\%$ (according to reference level)
	Spurious response	Two signals 3rd order intermodulation distortion: ≤ -70 dBc (10 MHz to 3 GHz, 10 MHz to 2.5 GHz with Option 22) *Frequency difference of two signals: ≥ 50 kHz, Pre-amplifier input*2: -55 dBm
1 dB gain compression	≥ -35 dBm (≥ 100 MHz, at pre-amplifier input*2)	

*1 Overall specification with pre-amplifier on (Noise figure is the simple performance.)

*2 Pre-amplifier input level = RF input level - RF ATT setting level

● **Option 10: Centronics interface**

Function	Outputs data to printer (Centronics standard). GPIB interface can not be installed simultaneously
Connector	D-sub 25-pin (jack)

● **Option 12: QP detector (MS2661B only)**

Functions	QP detection *Requires Option 02. When Option 12 installed, Option 02 RBW 100 Hz 3 dB bandwidth changed to 150 Hz (typical)
6 dB bandwidth	200 Hz, 9 kHz, 120 kHz Accuracy: $\pm 30\%$ (18° to 28°C)
Display	LOG scale, 5 dB/div (10 divisions) Linearity: $\leq \pm 2.0$ dB (0 to -40 dB, CW signal, reference level: 60 dB μ V, RF ATT: 0 dB, 18° to 28°C)

Pulse response characteristics	Response to CISPR pulse (DET mode: QP, 18° to 28°C)			
	Repetition frequency	Bandwidth		
		120 kHz	9 kHz	200 Hz
	1 kHz	≤-8.0 ±1.0 dB	≤-4.5 ±1.0 dB	-
	100 Hz	Referenced	Referenced	≤-4.0 ±1.0 dB
	60 Hz	-	-	≤-3.0 ±1.0 dB
	25 Hz	-	-	Referenced
	20 Hz	≤+9.0 ±1.0 dB	≤+6.5 ±1.0 dB	-
	10 Hz	≤+14.0 ±1.5 dB	≤+10.0 ±1.5 dB	≤+4.0 ±1.0 dB
2 Hz	≤+26.0 ±2.0 dB	≤+20.5 ±2.0 dB	≤+13.0 ±2.0 dB	
1 Hz	≤+28.5 ±2.0 dB	≤+22.5 ±2.0 dB	≤+17.0 ±2.0 dB	
QP on/off switching uncertainty (PEAK, QP)	≤±1.0 dB (CW signal, reference level - 40 dB, after auto-calibration, 18° to 28°C)			
Detection mode	QP, AVERAGE			
Field strength measurement	Waveform data compensation data display for specified antenna factor, field strength (dBμV/m) Built-in antenna factors: MP534A/651A Dipole Antenna, MP635A/666A Log-Periodic Antenna, MP414B Loop Antenna, user-defined (four types writable via GPIB or RS-232C, can be saved/loaded to/from memory card)			

●Option 13: QP detector (MS2651B only)

6 dB bandwidth	9, 120 kHz Accuracy: ±30% (18° to 28°C)		
Display	LOG scale, 5 dB/div (10 divisions) Linearity: ≤±2.0 dB (0 to -40 dB, CW signal, reference level: 60 dBμV, RF ATT: 0 dB, 18° to 28°C)		
Pulse response characteristics	Response to CISPR pulse (DET mode: QP, 18° to 28°C)		
	Repetition frequency	Bandwidth	
		120 kHz	9 kHz
	1 kHz	≤-8.0 ±1.0 dB	≤-4.5 ±1.0 dB
	100 Hz	Referenced	Referenced
	20 Hz	≤+9.0 ±1.0 dB	≤+6.5 ±1.0 dB
	10 Hz	≤+14.0 ±1.5 dB	≤+10.0 ±1.5 dB
	2 Hz	≤+26.0 ±2.0 dB	≤+20.5 ±2.0 dB
	1 Hz	≤+28.5 ±2.0 dB	≤+22.5 ±2.0 dB
QP ON/OFF Switching uncertainty (PEAK, QP)	≤±1.0 dB (CW signal, reference level - 40 dB, after auto-calibration, 18° to 28°C)		
Detection mode	QP, AVERAGE		
Field strength measurement	Waveform data compensation data display for specified antenna factor, field strength (dBμV/m) Built-in antenna factors: MP534A/651A Dipole Antenna, MP635A/666A Log-Periodic Antenna, MP414B Loop Antenna, user-defined (four types writable via GPIB or RS-232C, can be saved/loaded to/from memory card)		

●Option 14: PTA parallel I/O

Functions	Controls external devices from PTA, cannot be installed when Option 10 installed
System variables	As follows using PTA system variables IOA: Controls 8-bit parallel output port A IOB: Controls 8-bit parallel output port B IOC: Controls 4-bit parallel input/output port C IOD: Controls 4-bit parallel input/output port D EIO: Controls I/O switching of ports C/D EXO: Controls I/O trigger
PTL statements	External interrupt control of input to I/O ports using PTA-PTL statements IOEN statement: Enables interrupt input IODI statement: Disables interrupt input IOMA statement: Masks interrupt input ON TO GOTO statement: Changes program flow at interrupt generation ON TO GOSUB statement: Changes program flow at interrupt generation
Write strobe signal	Write strobe signal (negative pulse) output externally at control of output ports C/D
Power supply	External +5 ±0.5 Vdc (max. 100 mA) supply
Signal logic levels	Negative logic, TTL level Specified current: Output ports A/B (max. output current Hi: 2.6 mA, Lo: 24 mA) Output ports C/D (max. output current Hi: 15 mA, Lo: 24 mA) Other control output lines (max. output current Hi: 0.4 mA, Lo: 8 mA)
Connection cable connectors	Amphenol 36 pins

Connector pin layout	No.	Item	No.	Item
	1	GND	19	Output port B (6)
	2	Trigger input	20	Output port B (7) MSB
	3	Trigger output 1	21	I/O port C (0) LSB
	4	Trigger output 2	22	I/O port C (1)
	5	Output port A (0) LSB	23	I/O port C (2)
	6	Output port A (1)	24	I/O port C (3) MSB
	7	Output port A (2)	25	I/O port D (0) LSB
	8	Output port A (3)	26	I/O port D (1)
	9	Output port A (4)	27	I/O port D (2)
	10	Output port A (5)	28	I/O port D (3) MSB
	11	Output port A (6)	29	Port C status 0/1: I/O
	12	Output port A (7) MSB	30	Port D status 0/1: I/O
	13	Output port B (0) LSB	31	Write strobe signal
	14	Output port B (1)	32	Interruption signal
	15	Output port B (2)	33	Not used
	16	Output port B (3)	34	+5 V power supply
	17	Output port B (4)	35	Not used
18	Output port B (5)	36	Not used	

●Option 15: Sweep signal output

Sweep output (X)	0 to 10 V ± 1 V (≥ 100 k Ω termination, from left side to right side of display scale), BNC connector
Sweep status output (Z)	TTL level (low level with sweeping), BNC connector

●Option 19: DC coupled input (MS2661B only)

Functions	DC-couples input circuit of main unit and expands lower limit of receiver frequency range to 500 Hz *Can only be installed with narrow RBW (Option 02)
Electrical characteristics	The standard specifications of the main unit are supplemented and changed as follows: Frequency range: 500 Hz to 3 GHz Max. input level: +30 dBm (CW, RF ATT: ≥ 10 dB), ± 0 Vdc Average noise level: ≤ -80 dBm (500 Hz to 10 kHz), ≤ -90 dBm (10 kHz to 200 kHz), ≤ -110 dBm (200 kHz to 1 MHz) *RBW: 30 Hz, VBW: 1 Hz, RF ATT: 0 dB Frequency response: ± 1.2 dB (500 Hz to 100 kHz), ± 0.5 dB (100 kHz to 3 GHz) *Referenced to 100 MHz frequency, RF ATT: 10 dB, ambient temperature: 18° to 28°C

●Option 20: Tracking generator

Frequency range	9 kHz to 3 GHz
Output level range	0 to -60 dBm
Setting resolution	0.1 dB
Output level accuracy	$\leq \pm 1.0$ dB (at 100 MHz, 0 dBm)
Output level flatness	$\leq \pm 1.5$ dB (100 kHz to 3 GHz, output level: 0 dBm, referenced to 100 MHz frequency)
Output level linearity	$\leq \pm 1.0$ dB (0 to -30 dBm), $\leq \pm 2.0$ (-30 to -60 dBm) *100 kHz to 3 GHz, 0 dBm output level reference
Spurious	Harmonic: ≤ -20 dBc (100 kHz to 3 GHz) Non-harmonic: ≤ -35 dBc (100 kHz to 3 GHz)
Tracking generator feed through	≤ -95 dBm (spectrum analyzer input and tracking generator output connectors terminated at 50 Ω)
Output connector	N-J, 50 Ω

●Option 21: Television monitor (Multi)

Video	M-NTSC, B/G/H/I/D PAL, color
Audio	Simultaneous monitoring of video and audio *Needs Option 07
Functions	Channel: Automatic setting to broadcast wave of CCIR, Japan, USA, Italy, UK and China; automatic setting to CATV of CCIR, Japan and USA Trigger: Triggered sweep by V-SYNC, H-SYNC *Needs trigger/gate circuit (Option 06) Aux. output: Composite video signal, Connector: BNC

●Option 22: 75 Ω input (Option 12, 13, 19 and 20 can not be installed simultaneously.)

Frequency range		100 kHz to 2.5 GHz
Amplitude	Level measurement	Measurement range: Average noise level to +25 dBm (+133.8 dBμV) Max. input level: +25 dBm (+133.8 dBμV, CW average power, RF ATT: ≥10 dB), ±100 Vdc Residual response: ≤-95 dBm (+13.8 dBμV, RF ATT: 0 dB, input: 75 Ω terminated, 1 MHz to 2.5 GHz)
	Total level accuracy	±1.8 dB (100 kHz to 2.5 GHz, level measurement accuracy after calibration using internal calibration signal) Total level accuracy: Reference level accuracy (0 to -49.9 dBm) + frequency response + log linearity (0 to -20 dBm) + calibration signal source accuracy
	Reference level	Setting range Log scale: +8.8 to +133.8 dBμV, Linear scale: 274 μV to 4.87 V
	Frequency response	±1.0 dB (100 kHz to 2.5 GHz, referenced to 100 MHz, RF ATT: 10 dB, 18° to 28°C)
	Waveform display	Linearity (after calibration) Log scale: ±0.4 dB (0 to -20 dB, RBW: ≤1 MHz), ±1.0 dB (0 to -70 dB, RBW: ≤100 kHz), ±1.5 dB (0 to -85 dB, RBW: ≤3 kHz) Linear scale: ±4% (according to reference level) Marker level resolution Log scale: 0.01 dB Linear scale: 0.02% (according to reference level)
	Spurious response	2nd harmonic distortion (MS2651B): ≤-55 dBc (10 to 100 MHz, mixer input: -30 dBm), ≤-60 dBc (0.1 to 1.25 GHz, mixer input: -30 dBm) 2nd harmonic distortion (MS2661B): ≤-60 dBc (10 to 200 MHz, mixer input: -30 dBm), ≤-75 dBc (0.2 to 1.25 GHz, band 0, mixer input: -30 dBm), ≤-80 dBc (0.8 to 1 GHz, mixer input: -30 dBm) Two signals 3rd order intermodulation distortion (MS2651B): ≤-70 dBc (10 to 2.5 GHz) *Frequency difference of two signals: ≥50 kHz, mixer input: -30 dBm Two signals 3rd order intermodulation distortion (MS2661B): ≤-70 dBc (10 to 100 MHz), ≤-80 dBc (0.1 to 2.5 GHz) *Frequency difference of two signals: ≥50 kHz, mixer input: -30 dBm
Max. dynamic range	1 dB gain compression level to average noise level (MS2651B): >105 dB (0.1 to 1 GHz), >105 dB - f [GHz] dB (>1 GHz) 1 dB gain compression level to average noise level (MS2661B): >110 dB (0.1 to 1 GHz), >110 dB - f [GHz] dB (>1 GHz), >109 dB (0.1 to 1 GHz, with Option 08), >109 dB - 1.5f [GHz] dB (>1 GHz, with Option 08) Distortion characteristics (MS2651B, RBW: 1 kHz) 2nd harmonic: >67.5 dB (10 to 100 MHz), >70 dB (100 to 500 MHz), >70 - f [GHz] dB (0.5 to 1.25 GHz) 3rd order intermodulation: >76.6 dB (0.1 to 1 GHz), >76.6 dB - (2/3)f [GHz] dB (1 to 2.5 GHz) Distortion characteristics (MS2661B, RBW: 1 kHz) 2nd harmonic: >72.5 dB (10 to 200 MHz), >80 dB (200 to 500 MHz), >80 - f [GHz] dB (0.5 to 1.25 GHz), >82.5 - f [GHz] dB (0.8 to 1 GHz) 3rd order intermodulation: >80 dB (10 to 100 MHz), >83.3 dB (0.1 to 1 GHz), >83.3 dB - (2/3)f [GHz] dB (1 to 2.5 GHz)	
Functions	Input connector	NC-J, 75 Ω
	Auxiliary I/O	VIDEO OUTPUT (Y): 0 to 0.5 V ±0.1 V (typical, from lower edge to upper edge at 10 dB/div, 100 MHz, 75 Ω terminated) 0 to 0.4 V ±0.1 V (typical, from lower edge to upper edge at 10%/div, 100 MHz, 75 Ω terminated), BNC connector

●Option 23: 75 Ω tracking generator (Option 12, 13, 19 and 20 can not be installed simultaneously.)

Frequency range	100 kHz to 2.5 GHz
Output level range	+44 to +104 dBμV (setting resolution: 0.1 dB)
Output level accuracy	≤±1.5 dB (100 MHz, output level: +104 dBμV)
Output level flatness	≤±1.75 dB (100 kHz to 2.5 GHz, output level: +104 dBμV, referenced to 100 MHz)
Output level linearity	≤±1.0 dB (+74 to +104 dBμV), ≤±2.0 dB (+44 to +74 dBμV) *100 kHz to 2.5 GHz, referenced to +104 dBμV
Spurious	Harmonics: ≤-20 dBc (100 kHz to 2.5 GHz) Non-harmonics: ≤-30 dBc (100 kHz to 2.5 GHz)
Tracking generator feed through	≤13.8 dBμV (spectrum analyzer input and tracking generator output connectors terminated at 75 Ω)
Output connector	NC-J, 75 Ω

●Option 24: Television monitor (Brazil)

Video	M-NTSC, M PAL, color
Audio	Simultaneous monitoring of video and audio *Needs Option 07
Functions	Channel: Automatic setting to broadcast wave of CCIR, Japan and USA Automatic setting to CATV of CCIR, Japan and USA Trigger: Triggered sweep by V-SYNC, H-SYNC *Needs trigger/gate circuit (Option 06) Aux. output: Composite video signal, Connector: BNC

Ordering Information

Please specify model/order number, name and quantity when ordering.

Model/order No.	Name	Remarks
MS2651B MS2661B	- Main frame - Spectrum Analyzer Spectrum Analyzer	
	- Standard accessories -	
F0013	Power cord, 2.6 m:	1 pc
W1251AE	Fuse, 5 A:	2 pcs
B0329G	MS2650B, MS2660B/C series operation manual: Protective cover	1 copy 3/4MW4U
	- Options -	
MS2651B/2661B-01	Reference crystal oscillator	Stability: $\leq 2 \times 10^{-8}$ /day
MS2661B-02	Narrow resolution bandwidth	30, 100, 300 Hz (MS2661B only)
MS2651B/2661B-04	High-speed time domain sweep	1.25 μ s/div
MS2651B/2661B-06	Trigger/gate circuit	Pre-trigger and post trigger available
MS2651B/2661B-07	AM/FM demodulator	Outputs to loudspeaker or earphone connector
MS2651B/2661B-08	Pre-amplifier	100 kHz to 3 GHz, 20 dB
MS2651B/2661B-10	Centronics interface	GPIB cannot be installed simultaneously.
MS2661B-12	QP detector	Requires Option 02 (QP-BW: 0.2, 9, 120 kHz)
MS2651B-13	QP detector	QP-BW: 9, 120 kHz
MS2651B/2661B-14	PTA parallel I/O	Option 10 cannot be installed simultaneously.
MS2651B/2661B-15	Sweep signal output	X, Z
MS2661B-19	DC coupled input	MS2661B only, requires Option 02
MS2651B/2661B-20	Tracking generator	Built-in type
MS2651B/2661B-21	Television monitor (Multi)	M-NTSC, B/G/H/I/D PAL
MS2651B/2661B-22	75 Ω input	Option 12, 13, 19 and 20 can not be installed simultaneously.
MS2651B/2661B-23	75 Ω tracking generator	Option 12, 13, 19 and 20 can not be installed simultaneously.
MS2651B/2661B-24	Television monitor (Brazil)	M-NTSC, M PAL
	- Application parts -	
MX260002A	CDMA Cellular System Measurement Software	
MX260003A	PDC Measurement Software (for base station)	
MX260004A	GSM Measurement Software	
MX261001A	Low-Power Data Communication System Measurement Software conforming to issue of Direct Spread Spectrum System	
MX261002A	Low-Power Data Communication System Measurement Software conforming to issue of Frequency Hopping System	
MX262001A	CATV Measurement Software	
MX264001A	EMI Measurement Software	
J0561	Coaxial cord (N-P-5W · 5D-2W · N-P-5W), 1 m	
J0104A	Coaxial cord (BNC-P · RG-55/U · N-P), 1 m	
CSCJ-256K-SM	256 KB memory card	Meets PCMCIA Rel 2.0
CSCJ-512K-SM	512 KB memory card	Meets PCMCIA Rel 2.0
CSCJ-001M-SM	1024 KB memory card	Meets PCMCIA Rel 2.0
CSCJ-002M-SM	2048 KB memory card	Meets PCMCIA Rel 2.0
B0395A	Rack mount kit (IEC)	
B0395B	Rack mount kit (JIS)	
J0055	Coaxial adaptor (NC-P · BNC-J)	
J0076	Coaxial adaptor (NC-P · F-J)	
B0391A	Carrying case (hard type)	With casters
B0391B	Carrying case (hard type)	Without casters
MP612A	RF Fuse Holder	DC to 1000 MHz, 50 Ω (N)
MP613A	Fuse Element	For MP612A
J0805	DC block (Model 7003)	10 kHz to 18 GHz, ± 50 V, N-type, Weinschel product
MA2507A	DC Block Adaptor	50 Ω , 9 kHz to 3 GHz, ± 50 V, N-type
MA8601A	DC Block Adaptor	50 Ω , 30 kHz to 2 GHz, ± 50 V, N-type
MA8601J	DC Block Adaptor	75 Ω , 10 kHz to 2.2 GHz, ± 50 V, N-type
MA1621A	50 Ω \rightarrow 75 Ω Impedance Transformer	9 kHz to 3 GHz, ± 100 V, NC-type
MP614A	50 Ω \leftrightarrow 75 Ω Impedance Transformer	10 to 1200 MHz (transformer type), NC-type
J0121	Coaxial cord (NC-P-3W · 3C-2WS · NC-P-3W), 1 m	
J0308	Coaxial cord (BNC-P · 3C-2WS · NC-P-3W), 1 m	
J0063	Fixed attenuator for high power	30 dB, 10 W, DC to 12.4 GHz, N-type
J0395	Fixed attenuator for high power	30 dB, 30 W, DC to 9 GHz, N-type
MP640A	Branch	40 dB, DC to 1700 MHz
MP654A	Branch	30 dB, 0.8 to 3 GHz
MP520A	CM Directional Coupler	25 to 500 MHz, 75 Ω (NC)
MP520B	CM Directional Coupler	25 to 1000 MHz, 75 Ω (NC)
MP520C	CM Directional Coupler	25 to 500 MHz, 50 Ω (N)
MP520D	CM Directional Coupler	100 to 1700 MHz, 50 Ω (N)
MP526A	High Pass Filter	60 MHz band
MP526B	High Pass Filter	150 MHz band

Model/order No.	Name	Remarks
B0436A	Carrying case (soft type)	
MP526C	High Pass Filter	250 MHz band
MP526D	High Pass Filter	400 MHz band
MP526G	High Pass Filter	27 MHz band
MA1601A	High Pass Filter	800/900 MHz band, N-type
J0007	GPIB cable, 1 m	408JE-101
J0008	GPIB cable, 2 m	408JE-102
J0742A	RS-232C cable, 1 m	For PC-98 Personal Computer and VP-600, D-sub 25 pins (straight)
J0743A	RS-232C cable, 1 m	For AT compatible, D-sub 9-pins (cross)
60N50-1	Reflection bridge	50 Ω , N-P (measured-end) · N-J (I/O)
60NF50-1	Reflection bridge	50 Ω , N-J (measured-end) · N-J (I/O)
87A50	Reflection bridge	50 Ω , GPC-7 (measured-end) · N-J (I/O)
62N75	Reflection bridge	75 Ω , NC-P (measured-end) · NC-J (I/O)
62NF75	Reflection bridge	75 Ω , NC-J (measured-end) · NC-J (I/O)
MH648A	Pre-Amplifier	100 kHz to 1200 MHz
MP534A	Dipole Antenna	25 to 520 MHz
MP651A	Dipole Antenna	470 to 1700 MHz
BBA9106/VHA9103	Biconical Antenna	30 to 300 MHz
6502	Loop Antenna	10 kHz to 30 MHz
MP414B	Loop Antenna	9 kHz to 30 MHz
MP415B	Rod Antenna	9 kHz to 30 MHz
MP635A	Log-Periodic Antenna	80 to 1000 MHz
MP666A	Log-Periodic Antenna	200 to 2000 MHz
MB9A	Tripod	For MP534A/B, MP651A
MB19A	Tripod	For MP635A/666A
MA2601B	EMI Probe	
MA2601C	EMI Probe	
KT-10	EMI clamp	
KT-20	EMI clamp	



Specifications are subject to change without notice.

ANRITSU CORPORATION

5-10-27, Minamiazabu, Minato-ku, Tokyo 106-8570, Japan
 Phone: +81-3-3446-1111
 Telex: J34372
 Fax: +81-3-3442-0235

Overseas Subsidiaries

● U.S.A.

ANRITSU COMPANY

North American Region Headquarters
 1155 East Collins Blvd., Richardson, Tx 75081, U.S.A.
 Toll Free: 1-800-ANRITSU (267-4878)
 Phone: +1-972-644-1777
 Fax: +1-972-671-1877

● Canada

ANRITSU ELECTRONICS LTD.

Unit 102, 215 Stafford Road West
 Nepean, Ontario K2H 9C1, Canada
 Phone: +1-613-828-4090
 Fax: +1-613-828-5400

● Brazil

ANRITSU ELETRÔNICA LTDA.

Praia de Botafogo 440, Sala 2401 CEP 22250-040,
 Rio de Janeiro, RJ, Brasil
 Phone: +55-21-5276922
 Fax: +55-21-537-1456

● U.K.

ANRITSU LTD.

200 Capability Green, Luton, Bedfordshire LU1 3LU, U.K.
 Phone: +44-1582-433200
 Fax: +44-1582-731303

● Germany

ANRITSU GmbH

Grafenberger Allee 54-56, 40237 Düsseldorf, Germany
 Phone: +49-211-96855-0
 Fax: +49-211-96855-55

● France

ANRITSU S.A.

9, Avenue du Québec Z.A. de Courtabœuf 91951 Les
 Ulis Cedex, France
 Phone: +33-1-60-92-15-50
 Fax: +33-1-64-46-10-65

● Italy

ANRITSU S.p.A.

Via Elio Vittorini, 129, 00144 Roma EUR, Italy
 Phone: +39-06-509-9711
 Fax: +39-06-502-24-25

● Sweden

ANRITSU AB

Botvid Center, Filtija Backe 1-3 145 84 Stockholm,
 Sweden
 Phone: +46-853470700
 Fax: +46-853470730

● Singapore

ANRITSU PTE LTD.

6, New Industrial Rd., #06-01/02, Hoe Huat Industrial
 Building, Singapore 536199
 Phone: +65-282-2400
 Fax: +65-282-2533

● Hong Kong

ANRITSU COMPANY LTD.

Suite 719, 7/F., Chinachem Golden Plaza, 77 Mody
 Road, Tsimshatsui East, Kowloon, Hong Kong, China
 Phone: +852-2301-4980
 Fax: +852-2301-3545

● Korea

ANRITSU CORPORATION

14F Hyun, Juk Bldg. 832-41, Yeoksam-dong,
 Kangnam-ku, Seoul, Korea
 Phone: +82-2-553-6603
 Fax: +82-2-553-6604 to 6605

● Australia

ANRITSU PTY LTD.

Unit 3/170 Forster Road Mt. Waverley, Victoria, 3149,
 Australia
 Phone: +61-3-9558-8177
 Fax: +61-3-9558-8255

● Taiwan

ANRITSU COMPANY INC.

6F, 96, Sec. 3, Chien Kou North Rd. Taipei, Taiwan,
 R.O.C.
 Phone: +886-2-2515-6050
 Fax: +886-2-2509-5519